FP1216C-99

1200 Series, Addressable Fire Panel, 2-4 Loops, 16 Zone LED's, English UK

General

The FP1216C is a versatile addressable fire panel supplied with 2 class-A loops. In addition to a generous backlit LCD display, it provides LEDs for indicating both fire and fault conditions with text descriptions for 16 fire zones on the front panel user interface. The panel may be upgraded with an additional 2 class-A loops, full inter-panel networking facilities on both copper or fibre, as well as with a LON network bus that supports the Aritech LON700 devices and repeaters, amongst others.

The FP1216C provides extensive maintenance features, boasts powerful I/O programming and supports both Aritech 2000 and 900 series protocols.

Installer Friendly

The FP1216C offers multiple auto-configuration options with extensive auto detection facilities facilitating quick initial setup even for large systems. Multiple repeaters in various formats may be connected over a 2-wire network with both class-A and B operating modes, whilst up to 31 fire panels may be networked together for large applications.

User friendly

In addition to the comprehensive information LEDs, the panel's large LCD display allows for every device in the system to be described with up to 80 characters of descriptive text, as well as 40 characters for zone descriptions. Complete statistics and graphics indications for every device are available.

Several mechanisms for preventing false alarms, including floating background with automatic compensation, double knock and coincidence mode within and between zones, as well as soak test facilities allow the user complete piece of mind.

Maintenance friendly

Maintenance warnings are available whenever detectors reach contamination levels. Together with real time diagnostics and statistics per sensor, the FP1216C offers a wealth of in-depth information locally or by remote connections.

LON700 Modules

Up to 32 LON700 nodes are supported on the optional LON700 network. This includes LCD and LED repeaters, synoptic chart drivers, supervised in- and output boards, relay and open collector output boards, zone monitors and power supplies.



Details

- Configuration, maintenance and graphic PC software support
- Up to 128 device addresses per loop
- Full interpanel network options
- Full range of repeaters and LON700 devices including Dutch and Scandinavian fire brigade panels, and Scandinavian alarm delay units
- Networkable "black box" panels
- Power supply for 72-hour autonomy
- Default start-up and service modes
- Programmable service reminders, on-line diagnostics and statistics
- Maintenance warnings and soak testing facilties
- One-man maintenance
- Floating background and drift compenstation
- Programmable day/night functionality
- Coincidence within and between zones
- Timed and manual zone control
- I/O programming with Boolean functions (maximum allocated input memory = 300)
- Scandinavian variants with Scandinavian firemans key available
- EN54 and CPD certified

FP1216C-99

1200 Series, Addressable Fire Panel, 2-4 Loops, 16 Zone LED's, English UK

Technical specifications

General

Network size (nodes)	mere end 128

Electrical

Power consumption	200 VA
Operating voltage	21 to 28 VDC
Current consumption	200 mA @ 24 VDC
Mains supply	230 VAC (+10%, -15%), 47-63 Hz
Alarm current	<240 mA @ 24 VDC
Auxiliary supply (24 VDC)	9 to 28 VDC @ 1 A max.
Auxiliary supply (5 VDC)	5 VDC (±0.1V) 75 mA max.

Loop

Maximum loop capacity	4
Cable rating	Length: <2 km
Loops per panel	4 (Class A)/8 (Class B)
Loop current	<500 mA
Addresses per loop	<128 (protocol dependent)
Loop cable specification	Ø 1 mm, 300 nF/km, 100 ohm

Zone

Maximum zone capacity	fino a 255

Standby battery

Charging	27.3 VDC at 20°C, 36 mV/°C
Batteries supported in housing	2 x 12 V (7 to 45 Ah)

Physical

Form factor	Medium
Physical dimensions	445 x 445 x 120 mm (h x W x D)
Net weight	9 kg (no batteries)
Colour	Bianco (RAL 9016)
Mounting type	Montaggio a superficie

Environmental

Operating temperature	-5°C to +40°C
Storage temperature	-20°C to +60°C
IP rating	IP54

Regulatory

Certification	EN54-2, EN54-4

Inputs and outputs

Relays	4 (2 A @ 24 VDC - 60 W)
Supervised Relays	4 (24 VDC, 30 ohm, 120 nF, 500 m)
Inputs (Opto Isolated)	4 (15 VAC/0 to 28 VDC)
Inputs (Supervision selectable)	4
Zone indicators per panel	16 (fire & fault)

KIDDE COMMERCIAL

As a company of innovation, Kidde Global Solutions reserves the right to change product specifications without notice. For the latest product specifications, visit firesecurityproducts.com online or contact your sales representative.

Last updated on 26 November 2025 - 15:55